

## UNITED STATES PATENT APPLICATION

FOR

## NEW PEAK HOLD SCHEME

INVENTOR:

## HAJIME ANDOH

PREPARED BY:

W. DANIEL SWAYZE, JR.

TEXAS INSTRUMENTS, INC.

7839 CHURCHILL WAY, M/S 3999

DALLAS, TEXAS 75251

(972) 917-5633

InstA

## FIELD OF THE INVENTION

5           The present invention relates generally to peak detectors and more particularly to a peak detector for a small input signal.

## BACKGROUND OF THE INVENTION

10           In disks, such as DVD or DVD-RAM, information is recorded in sector units. A sector includes a header information area having a physical identification data and a user data area. The header information area is typically divided into a peak header area and a bottom header area, and user data is divided into land area and groove area. In DVD-RAM disks, a track is formed spirally, and the track is shifted laterally at a predetermined reference point. The reference point usually becomes a starting point of  
15           the first sector.

20           In DVD applications, peak detectors are used. An AC peak detector is non-linear circuit used to obtain a steady state amplitude at a level of the peak amplitude of the input AC signal. The input AC signal need not be a uniform sinusoidal or an infinite sum of sinusoidals such as in a square wave signal, but any signal with approximately complimentary positive and negative voltage peaks, such as communication data signal can be an AC signal.

25           A number of peak detector designs are known, however, each design has shortcomings which limit the range of operability and performance within that range. In particular, there is a need for peak detectors which detect peaks with amplitudes as low as 50 or even 20 millivolts. The known designs do not demonstrate acceptable

performance at such levels and more particularly has dead zones where a new peak is not recorded.

5 Figure 1 illustrates a peak hold circuit. An input signal is input to the base of transistor 100. A current flows from collector to base of collector 100. If the current exceeds the current flowing in the constant current source 102, current flows through capacitor 104 and charges up capacitor 104. The voltage on capacitor 104 is the peak hold voltage.

10 Figure 2 illustrates a typical input voltage. As discussed before, the input signal need not be sinusoidal. Figures 2 and 3 illustrates wave forms including the held voltage at the top of the wave form.

5 Figure 3 illustrates the relationship between the input amplitude and the peak hold voltage and the input amplitude. As can be very clearly seen, this circuit introduces a large amount of dead region that is not representative of the peak voltage.

[illegible]

5

## **BRIEF DESCRIPTION OF THE DRAWINGS**

Figure 1 illustrates a peak hold circuit.

5        Figure 2 illustrates an input signal.

Figure 3 illustrates a wave form showing the relationship between peak hold voltage/input amplitude and input amplitude.

10       Figure 4 illustrates a peak hold circuit of the present invention.

Figure 5 illustrates a wave form showing the relationship between peak hold voltage/input amplitude and input amplitude of the present invention.

15  
20  
25  
30  
35  
40  
45  
50  
55  
60  
65  
70  
75  
80  
85  
90  
95  
100  
105  
110  
115  
120  
125  
130  
135  
140  
145  
150  
155  
160  
165  
170  
175  
180  
185  
190  
195  
200  
205  
210  
215  
220  
225  
230  
235  
240  
245  
250  
255  
260  
265  
270  
275  
280  
285  
290  
295  
300  
305  
310  
315  
320  
325  
330  
335  
340  
345  
350  
355  
360  
365  
370  
375  
380  
385  
390  
395  
400  
405  
410  
415  
420  
425  
430  
435  
440  
445  
450  
455  
460  
465  
470  
475  
480  
485  
490  
495  
500

## DETAILED DESCRIPTION OF THE PRESENT INVENTION

Turning to Figure 4, an input signal which may be the input signal of Figure 2 is input to a track and hold circuit 400 through input terminal 410. The hold circuit tracks the input signal and holds it and outputs an output signal in accordance with a clock signal which is input. The output of the track and hold circuit 400 is input to capacitor 406, and capacitor 406 is connected to the track and hold circuit 400 and connected to ground. Connected in parallel to the capacitor 406 is constant current source 404. The constant current source 404 is connected to the track and hold circuit 400 and connected in parallel to the capacitor 406. The capacitor 406 forms a voltage from the charge resulting from the output of the track and hold circuit 400 and produces a peak hold voltage as an output voltage. The output of the track and hold circuit 400 is connected to the minus input of comparator 408. Additionally, the input signal is connected to the plus input of comparator 408. The output of comparator 408 is a series of pulses and is input to the clock input of the track and hold circuit 400.

In operation, the input signal is input to the track and hold circuit 400 as well as the comparator 408. The output from the track and hold circuit which corresponds to the current or old peak old voltage is input to the comparator, and a comparison is made within comparator 408 to compare the new peak with the old peak voltage. The comparator 408 produces an output pulse whenever the input signal is greater than the current or old peak voltage. This output from the comparator 408 is a series of pulses which is input to the clock input of the track and hold circuit 400. Thus, the track and hold circuit outputs the input voltage in accordance with the output of the comparator circuit 404. The peak hold voltage is formed on capacitor 406 and is held. During non-clock pulses, the voltage of capacitor 406 is discharged through current source 404. The present invention provides a high peak hold voltage for input amplitude as illustrated in Figure 5 with a small amount of dead region.